#### **Features**


- Non-contact switch has long life, high reliability, fast switching speed and low control power;
- Load current 2A 75VAC~264VAC
- (AC) Solid State Relay, Width only 15.7mm
- Photoelectric isolation, dielectric strength 2500VAC
- TTL compatible
- PCB mounting, also socket mounting (15 series)
- Environment-friendly product(RoHS compliant)
- Outline Dimensions:( 29.0×12.7×15.7)mm
- Main uses: electromagnetic valves, electric motors, incandescent
  lamps, communication and network equipment, computer terminal products,
  digital audio, video equipment, control systems, and instruments, medical devices, entertainment facilities, etc.;
- GB/T 36640-2018;IEC 62314:2006



INPUT SPECIFICATIONS (Ta=25°C)					
Control voltage range	5	(4~6) VDC			
	12	(9.6~14.4) VDC			
	24	(19.2~28.8) VDC			
Must turn-on voltage	5	4VDC			
	12	9.6VDC			
	24	19.2VDC			
Must turn-off voltage		1VDC			
Max. input current		10mA			
OUTPUT SPECIFICATIONS (Ta=25°C)					
Load voltage range		24VAC~280VAC			
Load current range		0.1~2A			
Max. surge current (10ms)		80A (10ms)			
Max. I²t for fusing (10ms A²S)		32			
Max. off-state leakage current		≤3mA (@220VAC)			
Max. on-state voltage drop		1.5Vr.m.s			
Max. turn-on time		Zerocross	≤1/2 Cycle+1ms		
		Random	≤1ms		
Max. turn-off time		≤1/2 Cycle+1ms			
Max. transient voltage		800V <sub>pK</sub>			
Min. off-state(dv/dt)		1000V/uS			
Max. zero-cross over voltage		±15V			
Min. power factor		0.5			


GENERAL SPECIFICATIONS (Ta=25°C)					
Dielectric strength(input to output)			2500VAC 50HZ/60HZ 1min		
Insulation resistance			1000MΩ (500VDC)		
Overvoltage (1.2/50uS)			4KV		
Mechanical performance	Shock	Functional	98m/s <sup>2</sup>		
	resistance	Destructive	980m/s <sup>2</sup>		
	Vibration resistance		10Hz~55Hz 1.5mm DA		
Operating temperature			-30℃~80℃		
Storage temperature			-40℃~100℃		
Ambient humidity			45%~85%		
Unit weight			Approx.13g		

#### ORDERING INFORMATION




 ${\Large \textbf{(8)} \ \textbf{Customer special code} \ : \ \textbf{numbers or letters denote customer's requirements},}$ 

# ■ Circuit diagram



### ■ OUTLINE DIMENSIONS, WIRING DIAGRAMOUTLINE


Unit: mm




Remark: (1) In case of no tolerance shown in outline dimension:outline dimension≤1mm,tolerance should be±0.2mm;outlinedimension>1mm and <5mm,tolerance should be ±0.3mm;outline dimension≥5mm,tolerance should be ±0.5mm.

(2) The tolerance without indicating for PCB layout is always ±0.1mm.

### ■ CHARACTERISTIC CURVES



Max. Permissible Non-repetitive Peak Surge Current vs. Continuance Time




Energizing Continuance Time (ms)

## **■** PRECAUTIONS

- 1. Soldering must be completed within 10s at 260°C or 5s at 350°C.
- 2. The SSR's case serves to dissipate the heat generated by the SSR itself. If poor ventilation is unavoidable, the load current must be derated. Please refer to the curve of Max. Load Current vs. Ambient Temperature for derating.
- 3. The internal input circuit of SSR does not have the reverse polarity protection, thus make sure the wiring of input and output and the input polarity is correct so as to avoid any damage to the SSR.
- 4. If the output transient voltage exceeds the nominal value, a varistor should be connected to the SSR's output

terminal in parallel to prevent the SSR being broken down. The recommended varistor voltage is 470V.

5. When the SSR is used for phase modulation, the time interval between the negative edge of the input pulse signal and the line voltage zero crossing point must last over 200µs, or it may be out of control.



- 6. Please do not use the SSR exceeding the limitation which is specified on this datasheet.
- 7. The specification is for reference only. Specifications subject to change without notice.